

CHANGING SETTINGS IN EUDORA® E-MAIL PROGRAMME TO THE TECH INFO INTERNET SERVICE.

The 33.6k modem number is:	(03) 9432 7222	The 56k modem number is:	(03) 9433 4444
Home page for TECH INFO is:	http://www.techinfo.com.au	Primary name server address:	203.63.149.1
Mail server name is (both POP3 & SMTP):	mail.techinfo.com.au	Secondary name server address:	203.63.149.2
Proxy server name is:	proxy.techinfo.com.au	on port:	8080
News server name is:	news.techinfo.com.au	on port:	119

These instructions are written for V2.0, V3.0 of Eudora and Eudora Lite. We assume that you have setup the dialler to connect to the TECH INFO internet service as part of the browser setup. Please complete the dialler setup before attempting this set of instructions.

1. Start **Eudora**.

2. Select **Tools**.
Select **Options**

Select **Getting Started** from the left side bar menu

Your **POP account** is **username@mail.techinfo.com.au**

(Please substitute **username** for the login name you have been allocated on the TECH INFO system.

Type in your **Real Name** in the space provided as it would appear in a typed document ie. **Fred Smith**

The connection method selected should be **Winsock**

Select **Personal Information** from the left side bar menu.

The first 2 items should already be filled in for you.

Item 3 - **Return address** should be entered in the format **username@techinfo.com.au** (substitute your login name for the word **username** in the text above)

Select **Hosts** from the left side bar menu

The POP name should already be filled in.

Type in the **SMTP address** as **mail.techinfo.com.au**

Ph should be blank.

Finger should be blank.

3. All other items in the setup menu are personal choices - leave them as set if you do not know what you are doing.

4. Please do not forget to change your **signature** file if it includes your old e-mail address as part of its text. To do this select **Tools** then **Signature**. Edit the file and save it by double clicking on the top left corner.