CHANGING SETTINGS OF MS EXPLORER 4.x & OUTLOOK EXPRESS® TO THE TECH INFO **INTERNET SERVICE.**

The 33.6k modem number is:	**(03) 9432 7222**	The 56k modem number is:	**(03) 9433 4444**
Home page for TECH INFO is:	**http://www.techinfo.com.au**	Primary name server address:	**203.63.149.1**
Mail server name is (both POP3 & SMTP):	**mail.techinfo.com.au**	Secondary name server address:	**203.63.149.2**
Proxy server name is:	**proxy.techinfo.com.au** on port: **8080**		
News server name is:	**news.techinfo.com.au** on port: **119**		

These instructions are written and intended for use with V4.x of MS Internet Explorer and MS Outlook Express. It is assumed that you have already installed this software and your modem and you may have used the your copy of MS Internet Explorer 4.x with another ISP previously although this is not important.

Go into **Control Panel** by selecting **'Start'**, **'Settings'**, **'Control Panel'**, then double click on the **'Internet'** icon.
Under the ***'General'*** tab. Type in the URL of the TECH INFO home page in the 'address' box as:- ***http://www.techinfo.com.au*** then click on **'Apply'**
Select the ***'Security'*** tab. Make sure 'medium' security is selected then click on **'Apply'**
Select the ***'Content'*** tab. Do not touch the 'Content Advisor' - (this will prevent Internet Explorer from working at all)
Click on ***'Connection'*** tab. Under **'connection'** click on **'connect to the Internet using a modem'** then click on **'settings'**. Click on **'Add'**. Under **'Type a name for the computer you are dialling'** type in '**Tech Info**' . Select your modem in the **'Select a device'** box, then press **'Next'**. Type in the **'Area code'** as **03** and the **'Telephone number'** as **9432-7222** for modems other than 56k and **9433-4444** for 56k modems. The **'Country code'** should be set to **Australia (61)** then press **'Next'** then click on **Finish**
Next click on **Properties**. Under the **General** tab, the Area code, Phone number should already be set. Put a tick in the box labelled **'use area code and dialling properties'**. At the bottom of the screen make sure your modem is selected in the **'Connect using'** box.
Under the '**Server types**' tab, the screen which appears should have **'Type of Dial-Up Server'** set as **PPP:Windows 95, WindowsNT, Internet** in the box.
On the rest of the screen, the boxes marked **'Enable software compression'** and **'TCP/IP'** (under protocols) are the only ones with ticks (or crosses) in them - all others are blank - remove the unwanted ticks by clicking on them one at a time.
Select **TCP / IP Settings** On the page which appears, there should be a "radio button" (a black dot) should be in **'Server assigned IP address'** and another in **'Specify name server address'**. In the **'Primary DNS'** type in (in place of the 0.0.0.0) **203.63.149.1** and in the **'Secondary DNS'** type in **203.63.149.2**. Both the **'Primary WINS'** and **'Secondary WINS'** should have **0.0.0.0** in them. Both the **'Use IP header compression'** and **'Use default gateway on remote network'** should have ticks in the box beside these options.
Press **OK** then **OK** to close off the Dial-Up Networking setup.

You should now be back in the **'Dial-up settings'** screen.
Under **'user'** type in your TECH INFO username eg. **fred**
Under **'password'** type in your TECH INFO assigned password
The **'Domain name'** is not required and should be blank. A tick should be in the box labelled **'disconnect if idle for xx minutes'**. The time should be set to **10** minutes. The box labelled **'connect automatically to update subscriptions'** should be blank. The box labelled **'perform security check before dialling'** should have a tick in it. Click on **'OK'** all these settings back to the **'Internet Properties'** screen.
Under the **'Proxy Server'** section, click on **'Access the internet using a proxy server'**, then click on **'Advanced'**
In the **'HTTP'** box at the top type in **proxy.techinfo.com.au** and in the **'port'** box to the right type in **8080** Make sure the box labelled **'Use the same proxy server for all protocols'** has an **X** in it. Click **'OK'** to finish. Click on **'Apply'** to save these changes.
Select the **'Programs'** tab. Select **'Outlook Express'** for both your Mail and News programs.
Select the **'Advanced'** tab. Do not change anything on this screen.
Select **'OK'** to save these changes and go back to the **'Control Panel'** screen. Click on the **X** at the top right hand corner of the dialogue box to close all open windows back to a clean screen.

MS OUTLOOK EXPRESS MAIL SETUP
From the Windows desktop screen, double click on **'Outlook Express'**. Select **'Tools'** then **'accounts'** Click on **'Add'** then select **'Mail'**
Enter under **'Display Name'** your real name eg. **Fred Smith** using upper and lower case as you choose. Click on **'Next'**
Under **'e-mail address'** type in your assigned e-mail address eg. **fred@techinfo.com.au**
Note that this is all in lower case with no spaces. Click on **'Next'**
At the top of this screen, the line should read **'Incoming mail server is a POP3 server'**
In the box labelled **'Incoming mail (POP3) server name'** is: **mail.techinfo.com.au**
The **'Outgoing (SMTP) server name'** is also: **mail.techinfo.com.au** Press **'Next'**
In this screen, where it says **'logon using'** , under the **'POP account name'** type in your username eg. **fred** Under password type in your TECH INFO assigned password. Press **'Next'**. In the **'Friendly Name'** screen, in the box labelled the **'Internet mail account name'** type in **Tech info Mail** then press **'Next'**
Make sure there is a black dot in the **'Connect using my phone line'**, then press **'Next**'.
Make sure there is a black dot in the **'Use an existing dial-up connection**', click on **Tech Info** in the box, then press **'Next'** , then **'Finish'**
Now click on the **'Properties'** button on the right hand side. Under **'Reply to'** address copy in your e-mail address es exactly as it is under **E-mail address**.

MS OUTLOOK EXPRESS NEWS-READER SETUP
Continuing on from the Mail setup above, to setup the News Reader, click on '**add**' , then select '**news**' Type in the **'Display Name'** as you want to see it, eg. **Fred Smith** as you want to see it using upper and lower case letters. After this press '**Next**'.
Under **'e-mail address'** type in your TECH INFO e-mail address eg. **fred@techinfo.com.au** then press '**Next**'
Type in the **News (NNTP) Server name** as: **news.techinfo.com.au**
The box labelled **'My news server requires me to log on'** should not have a tick in it. Press '**Next**' Under **'Internet News Account name'** type in **Tech info News'** then press **'Next'**
Make sure there is a black dot in the **'Connect using my phone line'** , then press **'Next'**
Make sure there is a black dot in the **'Use an existing dial-up connection**' click on **Tech Info** in the box, then press **'Next'** , then **'Finish'.**
Now click on the **'Properties'** button on the right hand side. Under **'Reply to'** address copy in your e-mail address es exactly as it is under **E-mail address**.
Next pick '**Close**' to complete the setup.
You are now setup to run your MS Explorer V4.x with the TECH INFO Internet service.
To connect to the Internet, simply double click on the **Internet** icon on the desktop screen (the blue 'e').

NOTE FOR WINDOWS NT USERS:-
By default, Windows NT sets "encrypted passwords" on. You must set this off for an NT machine to connect to the Internet.
To do this, after installing the software and creating an icon for TECH INFO, go into **Dial-up Networking**, select **More**, then **Edit entry and modem properties,** select the **Security** tab, and click on **Accept any authentication including clear text**, then save by clicking on **OK** and **Close**.